



# **UT-94**

Universal Transmitter Alarm/Trip Module

Masibus Model UT-94 is a 4 wire versatile universal transmitter that isolates & converts wide range of conventional / unconventional process inputs into standard process signals acceptable to commercially off the shelf (COTS) automation products. Signal inverting option is also available. The input circuit can accommodate a variety of input signal levels including bi-directional, reverse, true and live-zero.

A built in 4 digit display facilitates the user to monitor process value and helps in fast configuration and calibration. Model UT-94 enables analog signals to transmit without galvanic connections between the fields to the receiving instrument. This in turn allows ground or reference levels to float up to thousands of volts at its input terminals, and prevents circulating current between differing ground potentials that can contaminate input signal.

Isolation provided by Model UT-94 saves the control system from damage due to accidental application of high voltage or induced voltages on the input signal and in turn avoids wrong output signals to process. Isolation provides a good protection for sensitive system parts against voltage spikes etc.

Model UT-94 offers a wide range of input/ output signal types include mA, mV, V, RTD, TC, Resistance. Built-in transmitter power supply (TPS) can drive field transmitters in case of 4-20mA DC input. It offers excellent accuracy and stability for reliable operation in hostile environments and full isolation safely separates each input channel, each output channel and the power supply.

Model UT-94 is equipped with advanced functions like digital filtering, password setting, input and output protection and square root function for optimum process functionality.

## **Features**

- Compact DIN rail mounting
- Digital Display
- Easy configuration using keys & display
- Micro controller based transmitter
- Measuring Parameters: RTD, TC, mV, V, mA, Ω
- Dual Retransmission output
- Two Relay Output (Option)
- Modbus protocol on RS485 (Option)

### **Applications**

- Industrial process control
- Factory automation
- SCADA
- DAS
- Heat treatment furnaces
- Reheat furnaces
- Ceramic Kilns
- Glass Industry
- Water and waste water control

# **Technical Specifications**

| Input                  |   |  |  |  |  |  |  |
|------------------------|---|--|--|--|--|--|--|
| Input Type             | Thermocouple (E, J, K, T, B, R, S, N),<br>RTD (PT-100), mA ,mV, V &<br>Resistance |  |  |  |  |  |  |
| Display Range          | Refer Table-1   |  |  |  |  |  |  |
| Accuracy               | Refer Table-1   |  |  |  |  |  |  |
| ADC Resolution         | 17 bits   |  |  |  |  |  |  |
| Display Resolution     | 0.1 / 1°C   |  |  |  |  |  |  |
| Sampling Time          | < 75ms  |  |  |  |  |  |  |
| CJC Error              | ±2.0 °C Max   |  |  |  |  |  |  |
| Sensor Burnout current | 0.5uA   |  |  |  |  |  |  |
| RTD excitation current | 1mA Approx.   |  |  |  |  |  |  |
| NMRR                   | > 50 dB   |  |  |  |  |  |  |
| CMRR                   | > 120 dB  |  |  |  |  |  |  |
| Temp-co                | < 100ppm/°C   |  |  |  |  |  |  |
| Input Impedance        | > 1M $\Omega$ for Voltage,<br>100 $\Omega$ for Current                            |  |  |  |  |  |  |
| Max Voltage            | 20VDC   |  |  |  |  |  |  |
| Display & Keys         |   |  |  |  |  |  |  |
| Process Value          | 0.3" Four-digit Seven segment,<br>Red LED   |  |  |  |  |  |  |
| Status                 | Power, RL1, RL2, Tx, Rx   |  |  |  |  |  |  |
| Keys                   | 3 keys for configuration, calibration and operation                               |  |  |  |  |  |  |
| Output                 |   |  |  |  |  |  |  |
| Relay (Option)         |   |  |  |  |  |  |  |
| Relays                 | 2 Nos.  |  |  |  |  |  |  |
| Туре                   | Single Change over (C, NO, NC)  |  |  |  |  |  |  |
| Rating                 | 2A @ 230VAC / 30VDC   |  |  |  |  |  |  |
| A01                    | 4 20m A/ 0 20m A @ 7500 Mar   |  |  |  |  |  |  |
| Output Signal          | 4-20mA/ 0-20mA @ 750Ω Max.<br>1-5VDC/ 0-5VDC/ 0-10VDC @ 4KΩ Min.                  |  |  |  |  |  |  |
| Output accuracy        | ±0.25% of span  |  |  |  |  |  |  |
| Temp-co                | < 150ppm/°C   |  |  |  |  |  |  |
| AO2 (Option)           |   |  |  |  |  |  |  |
| Output Signal          | 4-20mA/ 0-20mA @ 750Ω Max.<br>1-5VDC/ 0-5VDC/ 0-10VDC @ 4KΩ Min.                  |  |  |  |  |  |  |
| Output accuracy        | ±0.25% of span  |  |  |  |  |  |  |
| Temp-co                | < 150ppm/°C   |  |  |  |  |  |  |
|                        |   |  |  |  |  |  |  |

#### **Communication (Option)** Interface RS485 (2 Wire) Modbus-RTU Protocol Baud rate 4800, 9600, 19200 24VDC (±1V) @30mA **Transmitter Power Supply** Power Supply

| Standard          | 85-265VAC/ 125-300VDC |
|-------------------|-----------------------|
| Optional          | 18-36VDC              |
| Power consumption | < 10 VA               |

#### Isolation (Withstanding voltage)

Between primary terminals\* and secondary terminals\*\*: At least 1500 V AC for 1 minute Between secondary terminals\*\*: At least 500 V AC for 1 minute \* Primary terminals indicate power terminals and relay output terminals. \*\* Secondary terminals indicate I/O terminals and Communication Port.

| Physical            |                        |
|---------------------|------------------------|
| Dimensions (mm)     | 75(H) x 55(W) x 110(D) |
| Mounting            | Din Rail               |
| Terminal Cable Size | 2.5 mm <sup>2</sup>    |
|                     |                        |

#### Environmental Operating temperature 0 to 55 °C Storage temperature 0 to 80 °C Humidity 20 to 95 % RH non-condensing

| Table 1: Display Range |               |                  |              |  |  |  |  |  |
|------------------------|---------------|------------------|--------------|--|--|--|--|--|
| Inpu                   | ut Type       | Ranges           | Accuracy     |  |  |  |  |  |
| Thermocouple           | E             | -200 to 1000 °C  | ±0.1% of FS  |  |  |  |  |  |
|                        | J             | -200 to 1200 °C  |              |  |  |  |  |  |
|                        | К             | -200 to 1370 °C  |              |  |  |  |  |  |
|                        | Т             | -200 to 400 °C   |              |  |  |  |  |  |
|                        | Ν             | -200 to 1300 °C  |              |  |  |  |  |  |
|                        | R             | 0 to 1750 °C     |              |  |  |  |  |  |
|                        | S             | 0 to 1750 °C     | ±0.25% of FS |  |  |  |  |  |
|                        | В             | 450 to 1800 °C   |              |  |  |  |  |  |
| RTD                    | Pt-100        | -199.9 to 850 °C |              |  |  |  |  |  |
| Voltage                | -10 to 500mV  |                  | ±0.1% of FS  |  |  |  |  |  |
|                        | 0/0.4 to 20mV |                  |              |  |  |  |  |  |
|                        | 0 to 5V       |                  |              |  |  |  |  |  |
|                        | 1 to 5V       | -1999 to 9999    |              |  |  |  |  |  |
|                        | 0 to 10V      |                  |              |  |  |  |  |  |
| Current                | 0/4 to 20mA   |                  |              |  |  |  |  |  |
| Resistance             | 0 to 2000Ω    |                  |              |  |  |  |  |  |

| Ordering Code |                |           |    |             |                  |     |   |         |       |      |               |       |
|---------------|----------------|-----------|----|-------------|------------------|-----|---|---------|-------|------|---------------|-------|
| Model         | Input Power St |           |    | ower Supply | NO. of AO & Type |     |   |         | Relay |      | Communication |       |
| UT94          | Х              |           | Х  |             | Х                |     | Х |         | Х     |      | Х             |       |
|               | 1              | E         | U1 | 85-265VAC/  | 1                | One | 1 | 4-20mA  | Ν     | None | Ν             | None  |
|               | 2              | J         |    | 125-300VDC  | 2                | Two | 2 | 0-20mA  | Υ     | Yes  | Y             | RS485 |
|               | 3              | К         | U2 | 18-36VDC    |                  |     | 3 | 1-5VDC  |       |      |               |       |
|               | 4              | Т         |    |             |                  |     | 4 | 0-5VDC  |       |      |               |       |
|               | 5              | В         |    |             |                  |     | 5 | 0-10VDC |       |      |               |       |
|               | 6              | R         |    |             |                  |     |   |         |       |      |               |       |
|               | 7              | S         |    |             |                  |     |   |         |       |      |               |       |
|               | 8              | N         |    |             |                  |     |   |         |       |      |               |       |
|               | 9              | Pt-100    |    |             |                  |     |   |         |       |      |               |       |
|               | С              | 4-20mA    |    |             |                  |     |   |         |       |      |               |       |
|               | D              | 0-20mA    |    |             |                  |     |   |         |       |      |               |       |
|               | E              | 1-5VDC    |    |             |                  |     |   |         |       |      |               |       |
|               | F              | 0-5VDC    |    |             |                  |     |   |         |       |      |               |       |
|               | G              | 0-10VDC   |    |             |                  |     |   |         |       |      |               |       |
|               | W              | 0.4-2VDC  |    |             |                  |     |   |         |       |      |               |       |
|               | Х              | -10-500mV |    |             |                  |     |   |         |       |      |               |       |
|               | Y              | 0-2V      |    |             |                  |     |   |         |       |      |               |       |
|               | Ζ              | 0-2000Ω   |    |             |                  |     |   |         |       |      |               |       |

#### Head Office:

Masibus Automation And Instrumentation Pvt. Ltd. B-30, GIDC Electronics Estate, Sector-25, Gandhinagar-382044, Gujarat, India. Tel: +91 79 23287275-79, Fax: +91 79 23287281-82. E-mail: sales@masibus.com, Web: www.masibus.com

All specifications are subject to change without notice due to continuous improvements. Doc. Ref. CB-2/UT94/R3F/0813

Masibus Representative: